

# DP Generators

## KIPOR

### IG3000



### DP Generators Buying Guide

Low noise level compared to more conventional models sets this unit apart from its competitors. One of the best sellers in its class, the lightweight design makes movement easier than equivalent models. This machine comes with two 3-pin round blue 16amp 230v sockets and a low oil level automatic shut off feature. Please feel free to browse the specification below and if you need any more information please don't hesitate to contact a member of our friendly team.

### Features and benefits:

- \*Maximum 3.00KVA output for wide range of applications.
- \*Low noise design, about 62~66dB/7m.
- \*Lightweight delivers super portability-only 60kg.
- \*6 hours running on a single fuel tank.
- \*Inverter technology delivers quality output.
- \*Stylish and patented design.
- \*Unique and patented air cycle system.
- \*Dual voltage and frequency output for ease of use.

### Specification:

Rated frequency (Hz)	50	60
Rated voltage(V)	230	120/240
Rated current (A)	12.2	23.3/11.7
Rated speed(r/min)	3600	
Rated output (kVA)	2.8	
Max. output (kVA)	3.0	
DC output	12V-8.3A	
Phase number	Single	

Current circuit breaker	Without
Structural type	Silent
Fuel capacity□L□	13
Set fuel consumption□g/kW.h□	480
Continuous running time (hr) (rated output)	6
Noise level (zero load--full load) dB (A)/7m	62-66
Overall dimension(L×W×H)□mm)	686×425×495
Net weight□kg□	60
Starting system	Recoil starter&Electric starter
Fuel type	Automotive unleaded gasoline
Lube oil type	CD grade or SAE10W30, 15W40
Engine model	KG205GETi
Engine type	Single cylinder, 4-stroke, air-cooled, OHV, gasoline engine
Bore×Stroke	68×54
Displacement(ml)	196
Compression ratio	8.5
Rated power[kW(Hp)]/(r/min)	4.0/3600
Ignition system	T.C.I
Spark plug	WR7DC
Lowest fuel consumption□g/kW.h□	395